



PO Box 31397
 BELLINGHAM, WA 98228-3517
 (T) 360-752-1610 • 888-841-1810
 (F) 360-752-1612 • 888-841-1812

WASATCH DOUBLE BATH MIRROR

HW KIT # 94-H325

PARTS LIST - SECTION A

- A. Hex Nut and Lock Washer (2)
- B. Socket Assembly (2)
- C. Image (Selected styles only) (1)
- D. 3/8" Machine Screws (9)
- E. Locking Hex Nut (9)
- F. Bracket Bar (2)
- G. Mirror (1)
- H. Cardboard Backing (1)
- I. Mirror Brackets (2)
- J. Tree Set (Selected Styles) (1)

SECTION A - FIXTURE ASSEMBLY

Note: Images on the fixture depends on the style of light.

1. Following diagram 1, slip the socket assembly wires through the lower hole in the frame. Secure the socket assembly (B) to the fixture back plate using the hex nut and lock washer set (A)
2. On selected styles, attach tree set (J) using 3/8" machine screws (D) and locking hex nuts (E). Next, attach image (C) using 3/8" machine screws (D) and locking hex nuts (E).
3. Following diagram 2, carefully place mirror (G) in fixture frame. Place the cardboard backing (H) over the back of the mirror.
4. Place the bracket bar (F) up the mirror brackets welded inside the fixture body.
5. Secure using machine screws (D) and locking hex nuts (E).
6. Proceed to section B.

GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended to be mounted to a minimum 4" x 1-1/8" deep round outlet box. The box must be directly supported by the building structure.
4. **Before starting the installation, disconnect the power by turning off the circuit breaker or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.**

NOTE: The important safeguards and instructions appearing in these instructions are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution, and care are factors, which cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

DIAGRAM 2



